

XEROX®

Technology | Document Management | Consulting Services

black-and-white laser printer

Laser performer for less

The Xerox Phaser 3428—the perfect laser printer for your office *and* budget. Enjoy fast, affordable, worry-free printing each and every business day. Providing a full-range of powerful features, including automatic two-sided printing, this handy printer will deliver complex print jobs in a snap.



Call today. For more information, call 1-877-362-6567 or visit us at www.xerox.com/office



CONFIGURATIONS	Phaser 3428D	Phaser 3428DN
Speed	Up to 30 ppm (Letter) / 28 ppm (A4)	
Duty Cycle	Up to 75,000 pages / month	
Paper Handling	Bypass Tray: 50 sheets, Size: Custom sizes from 3 x 5 in. (76 x 127 mm) to 8.5 x 14 in. (216 x 356 mm) Tray 1: 250 sheets, Size: Custom sizes from 3 x 5 in. (76 x 127 mm) to 8.5 x 14 in. (216 x 356 mm)	
Paper Input	Standard	Optional
	Tray 2: 250 sheets, Size: Custom sizes from 3 x 5 in. (76 x 127 mm) to 8.5 x 14 in. (216 x 356 mm)	
Paper Output	150 sheets (face-down), 1 sheet (face-up)	
Automatic 2-sided printing	Standard	
Print	As fast as 8.5 seconds	
First-Page-Out Time	Up to 1200 x 1200 Image Quality	
Print Resolution	400 MHz	
Processor	PCL 6, Accepts PCL5e data (no driver provided)	PCL6, Postscript, IBM Pro Printer, Epson emulations, Accepts PCL5e data (no driver provided)
Page Description Language (PDL)	Bi-directional Parallel, USB 2.0	Parallel, USB 2.0, Ethernet 10/100BaseTX
Connectivity	32 MB / 288 MB	64 MB / 320 MB
Memory (Std / Max)	Xerox Status Monitor, Watermarks, Booklet Printing, Poster Printing, N-Up, Fit to Page, Overlays, First Page Exception Page, Auto Tray Select, Toner Saver Mode	
Print Features		Embedded Web Server
Warranty	One Year Warranty	

DETAILED SPECIFICATIONS

Device Management

Phaser 3428D: Xerox Status Monitor
 Phaser 3428DN: CentreWare® IS Embedded Web Server, CentreWare Web, Xerox Status Monitor, Printer Settings Utility, SetIP

Print Drivers

Windows® 95/98/Me/NT 4.0/2000/XP/2003, Mac OS® 8.6-9.2/10.1-10.4, Linux: Red Hat®, Fedora™ Core, Mandrake™, SUSE®

*Phaser 3428/DN only

Media Handling

Bypass Tray: 16 to 43 lb. bond / 60 to 163 gsm
 Tray 1 *standard* and Tray 2 *optional*: 16 to 24 lb. bond / 60 to 90 gsm
 Media Types: Paper, Envelopes, Labels, Transparencies, Card Stock
 Two-sided Printing: Sizes: A4, Letter, Legal, Folio, Oficio, 20 to 24 lb. bond / 75 to 90 gsm

Operating Environment

Temperature: 50° to 90°F / 10° to 32°C
 Humidity: 20 to 80%

Electrical

Power: 100 – 127 V, 50/60 Hz
 220 – 240 V, 50/60 Hz
 Power Consumption: Average: 520 W, Standby: 75 W, Power Saver mode: 7 W, ENERGY STAR® Compliant
 Sound Pressure: Printing: 54 dB (A), Standby: 39 dB (A)
 Sound Power: Printing: 6.9 B, Standby: 5.0 B

Physical Dimensions (WxDxH)

15.8 x 17.4 x 11.1 in. / 401 x 442 x 281 mm
 Weight: 26.9 lb. / 12.2 kg

Supplies

Standard Toner –
 Black: Approx. 4,000 pages*
 106R01245
 High Capacity Toner –
 Black: Approx. 8,000 pages
 106R01246
*Declared yield in accordance with ISO/IEC 19752. Yield will vary based on image, area coverage and print mode.

Regulatory

FCC Part 15 Class B, Class 1 Laser Product, CE marked in accordance with Low Voltage Directive, 72/23/EEC and EMC Directive 89/336/EEC, CB Certified against IEC 60950

Productive, low-cost and easy-to-use laser printer for all your daily print needs

Outstanding office productivity

- Up to 30 ppm (letter) / 28 ppm (A4) laser printing, and as fast as 8.5 second first page out keeps up with your workload.
- A 400 MHz processor delivers complex pages fast.
- Two paper trays, plus an optional third tray, increases paper choice and capacity.
- Additional features such as watermarks, N-up, posters, and booklets give you eye-catching, customized results.
- Connect the way you want with USB and Parallel. For multiple users, 10/100BaseT Ethernet is standard on the Phaser 3428DN model.

Excellent value

- Affordable price lets you enhance your business potential without breaking your budget.
- Automatic two-sided printing saves time and paper.
- 1200 image quality resolution means crisp, professional printouts, while toner-saver mode will save money on less critical jobs.
- A compact design lets you put it where you need it.

Easy to use

- Installation is quick and easy – only four mouseclicks. And the status monitor will alert you if there are problems while printing.
- Remotely control, monitor, and diagnose your printer when connected to your network.
- Minimize supplies interaction with easy-to-install, high-yield toner cartridges.

