



# Xerox<sup>®</sup> VersaLink<sup>®</sup> C500 Colour Printer

VersaLink C500 Colour Printers are built on Xerox<sup>®</sup> ConnectKey<sup>®</sup> Technology. For more information, go to [www.connectkey.com](http://www.connectkey.com).

System Specifications	VersaLink C500/N	VersaLink C500/DN
<b>One-sided Speed</b> 8.5 x 11 in. A4 / 210 x 297 mm 8.5 x 14 in. / 216 x 356 mm	Up to 45 ppm colour and black and white Up to 43 ppm colour and black and white Up to 37 ppm colour and black and white	
<b>Two-sided Speed</b> 8.5 x 11 in. A4 / 210 x 297 mm 8.5 x 14 in. / 216 x 356 mm	NA	Up to 44 ppm colour and black and white Up to 42 ppm colour and black and white Up to 22 ppm colour and black and white
<b>Monthly Duty Cycle<sup>1</sup></b>	Up to 120,000 pages / month <sup>1</sup>	
<b>Recommended Average Monthly Print Volume<sup>2</sup></b>	Up to 8,000 pages	
<b>Hard Drive</b>	Optional 320 GB HDD	
<b>Processor</b>	1.05 GHz	
<b>Memory</b>	2 GB	
<b>Connectivity</b>	Ethernet 10/100/1000 Base-T, High-speed USB 3.0, Wi-Fi 802.11n and Wi-Fi Direct with optional Wi-Fi Kit (concurrent wired and wireless connections supported), NFC Tap-to-Pair	
<b>Controller Features</b>	Configuration Cloning, Xerox Extensible Interface Platform <sup>®</sup> , Xerox App Gallery, Xerox <sup>®</sup> Standard Accounting, Network Accounting Enabled, Role Based Permissions, Convenience Authentication Enabled, Online Support (accessed from the user interface and print driver)	
<b>User Interface Languages</b>	English, French, Italian, German, Spanish, Brazilian Portuguese, Russian, Dutch, Swedish, Danish, Finnish, Norwegian, Greek, Turkish, Polish, Czech, Hungarian, Romanian, Catalan, Ukrainian, Croatian	
<b>Device Specifications</b>		
<b>Electrical Requirements</b>		
<b>North America</b>	Voltage: 110-127V -10 % / +6 % Frequency: 50/60 Hz +/-3 %, 12A	
<b>Europe and Other Geographies</b>	Voltage: 220-240V +/- 10 % Frequency: 50 Hz +/-3 %, 8A	
<b>Power Consumption</b>		
<b>Continuous Printing<sup>4</sup></b>	730 watts or less	
<b>Ready / Standby Mode<sup>4</sup></b>	74 watts or less	
<b>Energy Saver / Sleep Mode<sup>4</sup></b>	.9 watts or less	

# Xerox® VersaLink® C500 Colour Printer

Operating Environment				
Required Temperature Range (Storage)	32° to 95° F (0° to 35° C)			
Required Temperature Range (Operating)	50° to 90° F (10° to 32° C)			
Required Relative Humidity	15% to 85%			
Sound Power Levels Operating Standby	7.17 B(A) or less 4.9 B(A) or less			
Sound Pressure Levels Operating Standby	56.2 dB(A) or less 33.6 dB(A) or less			
Boot Time (from Off to UI Ready)	As fast as 52 seconds			
Warm-up Time (from Sleep to UI Ready)	As fast as 11 seconds			
Dimensions and Weight (Unpackaged)	Width	Depth	Height	Weight
VersaLink C500/N	16.9 in. / 427.4 mm	18.4 in. / 465.5 mm	17.5 in. / 443.4 mm	61 lb. / 27.6 kg
VersaLink C500/DN	16.9 in. / 427.4 mm	18.4 in. / 465.5 mm	17.5 in. / 443.4 mm	61 lb. / 27.6 kg
550-sheet Paper Tray	16.5 in. / 420 mm	18.3 in. / 464.5 mm	4.8 in. / 123 mm	4.1 lb. / 6.6 kg
High Capacity Feeder	28.5 in. / 724.2 mm	30.4 in. / 772.1 mm	18.1 in. / 459 mm	43.4 lb. / 19.7 kg
Stand	28.5 in. / 724.2 mm	30.4 in. / 772.1 mm	13.2 in. / 336 mm	37 lb. / 16.6 kg
Caster Base	28.5 in. / 724.2 mm	30.4 in. / 772.1 mm	3.5 in. / 90 mm	18.7 lb. / 8.5 kg
Dimensions and Weight (Packaged)	Width	Depth	Height	Weight
VersaLink C500/N	22.8 in. / 580 mm	25 in. / 634 mm	23.9 in. / 607 mm	75 lb. / 34 kg
VersaLink C500/DN	22.8 in. / 580 mm	25 in. / 634 mm	23.9 in. / 607 mm	75 lb. / 34 kg
550-sheet Paper Tray	21.1 in. / 535 mm	23 in. / 584 mm	9.8 in. / 248 mm	18.7 lb. / 8.5 kg
High Capacity Feeder	22.4 in. / 568 mm	26.1 in. / 663 mm	28 in. / 711 mm	83.8 lb. / 38 kg
Stand	23 in. / 584 mm	24.8 in. / 629 mm	23.5 in. / 597 mm	57.3 lb. / 28 kg
Caster Base	23 in. / 585 mm	24.4 in. / 619 mm	13 in. / 330 mm	39.7 lb. / 18 kg
Certifications				
	To view the latest list of certifications, go to <a href="http://www.xerox.com/OfficeCertifications">www.xerox.com/OfficeCertifications</a> .			
Print				
First-print-out Time	As fast as 10 seconds colour / 8.5 seconds black and white			
Print Resolution	Up to 1200 x 2400 dpi			
Page Description Languages	PCL® 5e, 6 PDF XPS TIFF JPEG HP-GL Adobe® PostScript® 3™			
Maximum Print Area	4 mm from edge of paper			

## Xerox® VersaLink® C500 Colour Printer

<b>Print Features</b>	<ul style="list-style-type: none"> <li>Application Defaults</li> <li>Banner Pages Enable / Disable</li> <li>Bi-directional Real-time Status</li> <li>Booklet Layout</li> <li>Color Adjustments (lightness, contrast, saturation, color balance)</li> <li>Color Correction</li> <li>Draft Mode</li> <li>Fit to new paper size</li> <li>Job Identification (Print ID or Banner, Print ID in margins on first page only or all pages)</li> <li>Job Monitoring (Client or Local User Interface)</li> <li>N-up Page Layout (up to 16 pages per sheet)</li> <li>Paper Selection by Attribute</li> <li>Personal Print</li> <li>Print Around Enable / Disable</li> <li>Print from USB</li> <li>Run Black</li> <li>Sample Set</li> <li>Saved Job</li> <li>Scaling</li> <li>Secure Print</li> <li>Skip Blank Pages</li> <li>Special Pages (exception page programming: covers, inserts, exceptions pages)</li> <li>Store and Recall Driver Settings</li> <li>Stored Jobs Deletion</li> <li>Two-sided Printing (as default – DN configuration)</li> <li>Watermark (predefined and custom)</li> <li>Xerox® Earth Smart Driver Settings</li> </ul>
<b>Print from USB</b>	<ul style="list-style-type: none"> <li>Allows walk-up printing from Type A USB port</li> <li>Supports direct printing from computer via Type B USB port</li> <li>Supported file formats: PDF, JPEG, TIFF, XPS, PDF/A</li> </ul>
<b>Operating Systems</b>	<ul style="list-style-type: none"> <li>Windows® 7, 8, 8.1, 10</li> <li>Windows Server 2008 SP2, Server 2008 R2 SP1, Server 2012, Server 2012 R2, Server 2016</li> <li>macOS® 10.11, 10.12, 10.13</li> <li>Citrix®</li> <li>Redhat® Enterprise Linux®</li> <li>Fedora Core</li> <li>IBM® AIX®</li> <li>HP-UX®</li> <li>Oracle® Solaris</li> <li>SUSE®</li> <li>SAP®</li> </ul> <p>Note: For information about supported versions for the above operating systems, please visit our Drivers &amp; Downloads page and specify your device at <a href="http://www.support.xerox.com">www.support.xerox.com</a>.</p>
<b>Fonts</b>	<ul style="list-style-type: none"> <li>PostScript fonts: 136</li> <li>PCL fonts: 83</li> </ul>
<b>Xerox® Mobile Express Driver®</b>	<p>Makes it easy for mobile users to find, use and manage Xerox® and non-Xerox® devices in every new location. Plug into a new network, and Mobile Express Driver automatically discovers available printers and provides status and capability information. Save a list of “favorite” printers for each location, store application print settings for use on any printer in any network, and greatly reduce mobile support calls to IT.</p>
<b>Xerox® Global Print Driver®</b>	<p>A truly universal print driver that lets IT administrators install, upgrade and manage Xerox® and non-Xerox® devices from a single driver. It provides a consistent, easy-to-use interface for end-users, reducing the number of support calls, and simplifying print services management.</p>
<b>Xerox® Pull Print Driver</b>	<p>Makes it easy for IT managers to qualify, deploy and manage all print devices using a single driver in a Pull Print environment. Uses a single queue and single driver. The Xerox® Pull Print Driver extends convenience across a broad range of printing assets. IT administrators no longer need to manage and configure multiple drivers. Used in conjunction with Equitrac Office®, Ysoft® SafeQ®, Pharos® and others.</p>

# Xerox® VersaLink® C500 Colour Printer

Mobile Solutions and Mobile Device Apps	
<b>Apple® AirPrint®</b>	Print email, photos and important office documents directly from an Apple iPhone® or iPad® with no drivers to install and no cables to connect. With AirPrint, an iPhone or iPad automatically locates and connects to the AirPrint-enabled device over the office Wi-Fi network.
<b>Google Cloud Print™</b>	Google Cloud Print connects print devices to the web, enabling users to print the applications they use every day from smartphones, tablets, Chromebook™ notebook computers and any other web-connected device.
<b>@PrintByXerox</b>	@PrintByXerox is a free service that allows secure printing from any email-enabled device (computer, phone, tablet, iOS, Android™, Google® Chromebook™ and more) to a Xerox® printer or MFP using a single email address with no IT intervention. No training is needed. End-users simply send attachments to the email address, and release them at the MFP panel.
<b>Xerox® Print Service Plug-in for Android™ (Free at Google Play™ Store)</b>	The Xerox® Print Service Plug-in for Android KitKat (4.4 or greater) devices streamlines mobile printing without third-party apps or additional print drivers. You can easily print photos, Web pages and documents when your mobile device is connected to printers or multifunction printers using a wireless network. A robust print option set includes two-sided printing, stapling and secure code release. A free download is available from the Google Play™ store.
<b>Xerox® Print Management and Mobility Suite, Xerox® Print Management and Mobility Service</b>	Xerox® Print Management and Mobility Suite is a modular set of workflows designed to save customers time and money by providing effective control over their print fleet, while enabling worker productivity and mobility through a set of robust workflows. Xerox enables ultimate customer flexibility by offering these capabilities in both an on-premises server version and with a cloud based-version of this solution.
Software Solutions	
<b>Xerox® ConnectKey® Apps (Found at the Xerox® App Gallery)</b>	Increase user productivity by simplifying and shortening everyday tasks. Unlike traditional software, ConnectKey Apps do not require a dedicated server, PC or IT resource. Instead, simply download these lightweight, serverless ConnectKey Apps to the ConnectKey-enabled device.
Security	
<b>Security Features</b>	<ul style="list-style-type: none"> <li>Access Controls</li> <li>AES 256-bit Encryption</li> <li>Audit Log</li> <li>Certificate Path Validation</li> <li>Certificate Revocation List (CRL)/Status Protocol (OCSP)</li> <li>Detection of external program falsification (XCP Plug-in)</li> <li>Cisco® Identity Services Engine (ISE) Integration</li> <li>Domain Filtering</li> <li>FIPS 140-2</li> <li>Firmware Verification</li> <li>Immediate Disk Overwrite*</li> <li>IP Address Filtering</li> <li>IPsec</li> <li>Network Authentication</li> <li>Port Filtering</li> <li>Pre-installed Self-Signed Certificates</li> <li>Role Based Permissions</li> <li>Secure Print</li> <li>Security Certificate Management</li> <li>Smart Card Enablement (CAC/PIV/.NET)</li> <li>SNMPv3</li> <li>Status Protocol (OCSP)</li> <li>TLS/SSL</li> </ul> <p>*Requires HDD/Productivity Kit</p>

# Xerox® VersaLink® C500 Colour Printer

Accounting	
<b>Xerox® Standard Accounting / Network Accounting (Standard)</b>	
<b>Tracking</b>	Print usage
<b>Accounting</b>	<p>Xerox® Standard Accounting Tool            Up to 1,000 User Accounts without HDD            Up to 9,999 User Accounts with HDD            Up to 500 General accounts</p> <p>Network Accounting (Job Based Accounting)            Up to 1,000 User IDs; Up to 1,000 Account IDs without HDD            Up to 60,000 User IDs; Up to 60,000 Account IDs with HDD            Up to 14,000 accounting records (transactions)</p>
<b>Features</b>	Administrator can manage the feature via the Embedded Web Server.
<b>Accounting Options – Network Accounting (Allows central server to manage all accounting)</b>	
	<ul style="list-style-type: none"> <li>• Enhanced network accounting with up to the minute data on how the system is being used</li> <li>• Comprehensive management and enterprise scale tracking and reporting of device usage</li> <li>• Numerous solutions are available through Xerox Alliance Partners. For details visit <a href="http://www.xerox.com">www.xerox.com</a></li> <li>• Security enhancements include simultaneous support for HTTP/HTTPS protocols</li> <li>• Device requests account authentication from third party server enabling larger databases of users and accounts</li> <li>• Accept Authentication Login at control panel and pass to third party Networking Account</li> </ul>
Paper Handling	
<b>Bypass Tray</b>	
<b>Capacity<sup>3</sup></b>	150 sheets
<b>Sizes</b>	Custom sizes: 3 x 5 in. to 8.5 x 14 in. / 76 x 127 mm to 216 x 356 mm
<b>Weights</b> One-sided: Two-sided:	16 lb. bond to 80 lb. cover / 60 to 220 gsm 16 lb. bond to 65 lb. cover / 60 to 176 gsm
<b>Types</b>	Bond Plain Paper Cardstock Custom Envelopes Hole Punched Labels Letterhead Lightweight Cardstock Pre-Printed Recycled
<b>Tray 1</b>	
<b>Capacity<sup>3</sup></b>	550 sheets
<b>Sizes</b>	Custom sizes: 3 x 7.5 in. to 8.5 x 14 in. / 76 x 190 mm to 216 x 356 mm
<b>Weights</b> One-sided: Two-sided:	16 lb. bond to 80 lb. cover / 60 to 220 gsm 16 lb. bond to 65 lb. cover / 60 to 176 gsm

# Xerox® VersaLink® C500 Colour Printer

<b>Types</b>	Bond Plain Paper Cardstock Custom Hole Punched Labels Letterhead Lightweight Cardstock Heavyweight Cardstock Pre-Printed Recycled Envelope	
<b>Up to Four Additional Trays (Optional)</b>		
<b>Capacity<sup>3</sup></b>	550 sheets	
<b>Sizes</b>	Custom sizes: 3 x 7.5 in. to 8.5 x 14 in. / 76 x 190 mm to 216 x 356 mm	
<b>Weights</b> One-sided: Two-sided:	16 lb. bond to 80 lb. cover / 60 to 220 gsm 16 lb. bond to 65 lb. cover / 60 to 176 gsm	
<b>Types</b>	Bond Plain Paper Cardstock Custom Hole Punched Labels Letterhead Lightweight Cardstock Heavyweight Cardstock Pre-Printed Recycled	
<b>High Capacity Feeder (Optional)</b>		
<b>Capacity<sup>3</sup></b>	2,000 sheets	
<b>Sizes</b>	Letter/A4	
<b>Weights</b> One-sided: Two-sided:	16 lb. bond to 65 lb. cover / 60 to 176 gsm 16 lb. bond to 65 lb. cover / 60 to 176 gsm	
<b>Types</b>	Bond Plain Paper Hole Punched Letterhead Lightweight Cardstock Pre-Printed Recycled	
<b>Total Capacity</b>		
<b>Standard Device Capacity<sup>3</sup></b>	700 sheets	
<b>Total Device Capacity<sup>3</sup></b>	3,250 sheets	
<b>Paper Output</b>		
<b>Output Capacity<sup>3</sup></b>	500 sheets	
<b>Automatic Two-sided Printing</b>	NA	Standard

# Xerox® VersaLink® C500 Colour Printer

Device Management	
<b>Network Protocols</b>	TCP/IP: HTTP/HTTPS, Internet Printing Protocol, LPR/LPD, Raw Socket Printing/Port 9100, IPv4/IPv6, WSD LDAP Bonjour® / AirPrint™ Most protocols not in use can be disabled
<b>Administrative Protocols</b>	DHCP, SNMP, WINS, HTTP, HTTPS, TLS, SNTP, MDNS
Xerox® CentreWare® Web Software	
	<ul style="list-style-type: none"> <li>• A Web-based server application for network administrators that permits web browser-based device management from any workstation, whether running Windows or UNIX or any other operating system</li> <li>• Works with any SNMP-managed printer from any manufacturer</li> <li>• Provides help with device discovery and installations, health checks and troubleshooting, and device upgrades, as well as basic accounting and asset management</li> </ul>
Xerox® Embedded Web Server – Integrated Device Web Page	
<b>Device Status</b>	<ul style="list-style-type: none"> <li>• Tray status/contents</li> <li>• Consumables status</li> <li>• Billing/Usage</li> <li>• Quick Links</li> <li>• Online Support</li> </ul>
<b>Print Queue Viewing</b>	Job print queue management—view and delete
<b>Job Submission</b>	Print-ready files (PS, PCL, PDF, XPS, JPEG)
<b>Device Administration</b>	Allows simple, remote installation setting of configuration options and management of the device
<b>Browsers</b>	Microsoft® Internet Explorer® Microsoft Edge™ Mozilla™ Firefox® Apple® Safari® Google Chrome™
Remote Services	
<b>Xerox® Meter Assistant® Service</b>	Automates the process of collecting and submitting meter reads for tracking and billing of Xerox® device usage. Eliminates the need for time-consuming end-user involvement and ensures that meter reads are submitted to Xerox on time.
<b>Xerox® Supplies Assistant® Service</b>	Automatically orders supplies for Xerox® output devices based on actual usage, eliminating the need to manually manage supplies inventory.
<b>MaintenanceAssistant</b>	Offers a fast (and free) way to resolve potential issues and receive assistance and automate the troubleshooting/repair process. Diagnostic data is sent to Xerox, allowing for problems to be solved faster with increased uptime.
What's In The Box	
	VersaLink C500 Colour Printer Starter Capacity Print Cartridge: One of each (Cyan, Magenta, Yellow: 2,400 print capacity <sup>5</sup> , Black: 5,000 print capacity <sup>5</sup> Software and Documentation CD (Safety, Regulatory, Recycling and Disposal Guides, Print Drivers, and Warranty Statement) Installation Guide Quick Use Guides Power cord

# Xerox® VersaLink® C500 Colour Printer

Supplies and Accessories	Quantity	Part Number
<b>Supplies</b>		
<b>Standard Capacity Print Cartridges</b>	Black: 5,000 standard pages <sup>5</sup> Cyan: 2,400 standard pages <sup>5</sup> Magenta: 2,400 standard pages <sup>5</sup> Yellow: 2,400 standard pages <sup>5</sup>	106R03880 106R03877 106R03878 106R03879
<b>High Capacity Print Cartridges</b>	Black 12,100 standard pages <sup>5</sup> Cyan: 5,200 standard pages <sup>5</sup> Magenta: 5,200 standard pages <sup>5</sup> Yellow: 5,200 standard pages <sup>5</sup>	106R03887 106R03881 106R03882 106R03883
<b>Extra High Capacity Print Cartridges</b>	Cyan: 9,000 standard pages <sup>6</sup> Magenta: 9,000 standard pages <sup>6</sup> Yellow: 9,000 standard pages <sup>6</sup>	106R03884 106R03885 106R03886
<b>Routine Maintenance Items</b>		
<b>Drum Cartridges</b>	Cyan: 40,000 pages <sup>6</sup> Magenta: 40,000 pages <sup>6</sup> Yellow: 40,000 pages <sup>6</sup> Black: 40,000 pages <sup>6</sup>	108R01481 108R01482 108R01483 108R01484
<b>Waste Cartridge</b>	30,000 pages <sup>6</sup>	108R01416
<b>Accessories</b>		
<b>550-sheet Feeder</b>		097S04949
<b>2,000-sheet High Capacity Feeder (includes Stand/Caster Base)</b>		097S04948
<b>Cabinet (includes Stand/Caster Base)</b>		097S04955
<b>Stand/Caster Base</b>		097S04954
<b>Productivity Kit with 320 GB HDD</b>		497K18360
<b>Wireless Network Adapter (Wi-Fi Kit)</b>		497K16750

<sup>1</sup> Maximum volume capacity expected in any one month. Not expected to be sustained on a regular basis.

<sup>2</sup> Expected regular monthly throughput.

<sup>3</sup> Paper capacities are based on 20 lb. / 75 gsm stock; capacities will vary with different weight stocks.

<sup>4</sup> Power states defined per ENERGY STAR® Programme requirements for Imaging Equipment.

<sup>5</sup> Average standard pages. Declared Yield in accordance with ISO/IEC 19798. Yield will vary based on image, area coverage and print mode.

<sup>6</sup> Approximate pages. Declared yield will vary depending on job run length, media size/orientation and machine speed. For more information visit: <http://www.office.xerox.com/latest/SUPGL-01.pdf>.

Return spent imaging supplies through the Xerox Green World Alliance collection/reuse/recycling programme. For more information, visit [www.xerox.com/about-xerox/recycling](http://www.xerox.com/about-xerox/recycling).

For more information, visit us at [www.xerox.com/office](http://www.xerox.com/office)

Configurations vary by geography.

