

Xerox® VersaLink® C8000 Colour Printer



The VersaLink® C8000 Colour Printer is built on Xerox® ConnectKey® Technology. For more information, go to www.ConnectKey.com.

System Specifications	VersaLink® C8000DT
One-Sided Speed A4 A4 SEF 216 x 356 mm A3 / 297 x 420 mm / SRA3 / 320 x 450 mm	Up to 45 ppm (pages per minute) long edge feed (LEF) Up to 32 ppm Up to 26 ppm Up to 22 ppm
Two-Sided Speed A4 A4 SEF 216 x 356 mm A3 / 297 x 420 mm / SRA3 / 320 x 450 mm	Up to 45 ppm LEF Up to 32 ppm Up to 17 ppm Up to 15 ppm
Monthly Duty Cycle¹	Up to 205,000 pages / month
Recommended Average Monthly Print Volume²	Up to 20,000 pages per month
Hard Drive	320 GB HDD (Optional)
Processor	1.6 GHz Dual-Core
Memory	4 GB
Connectivity	Ethernet 10/100/1000 Base-T, High-speed USB 3.0, Wi-Fi 802.11n/g/b/a and Wi-Fi Direct with optional Wi-Fi Kit (concurrent wired and wireless connections supported), NFC Tap-to-Pair
Controller Features	Configuration Cloning, Xerox Extensible Interface Platform®, Xerox App Gallery, Xerox® Standard Accounting, Network Accounting Enabled, Role Based Permissions, Convenience Authentication Enabled
User Interface Languages	English, French, Italian, German, Spanish, Brazilian Portuguese, Russian, Dutch, Swedish, Danish, Finnish, Norwegian, Greek, Turkish, Polish, Czech, Hungarian, Romanian, Catalan

Xerox® VersaLink® C8000 Colour Printer

Device Specifications				
Electrical Requirements				
Europe and Other Geographies	Voltage: 220-240V +/- 10 % Frequency: 50/60 Hz +/-3 %, 10A			
Power Consumption				
Printing ³	2.32 kWh			
Standby Mode ³	73.8 Watts or less			
Sleep Mode ³	0.53 watts or less			
Operating Environment				
Required Temperature Range (Storage)	Below 48° C, and in compliance with MN2-810.13			
Required Temperature Range (Operating)	10° to 28° C Must be 28° C or below if humidity is at 85 %			
Required Relative Humidity	15 % to 85 % Must be 62.5 % or below at 32° C			
Sound Power Levels	Printing: 6.63 B(A) or less Standby: 3.24 B(A) or less Full System (including finisher) Printing: 7.56 B(A) Standby: 3.36 B(A)			
Sound Pressure Levels	Printing: 56.8 dB or less Standby: 15.4 dB or less Full System (including finisher) Printing: 57.1 dB Standby: 15.2 dB			
Boot Time (from Off to UI Ready)	Less than 60 seconds			
Warm-up Time (from Sleep to UI Ready)	Less than 10 seconds (without HDD) Less than 16 seconds (with HDD)			
Dimensions and Weight (Unpackaged)	Width	Depth	Height	Weight
VersaLink® C8000/DT	620 mm	723 mm	809.3 mm	80.8 kg
Two Tray Module	668.5 mm	723 mm	261.2 mm	27.2 kg
Tandem Tray Module	668.5 mm	723 mm	261.2 mm	33.8 kg
High Capacity Feeder	389 mm	602.9 mm	380.01 mm	29.0 kg
Office Finisher	559.8 mm	552 mm	1012 mm	28.0 kg
Booklet Maker Finisher	298.5 mm	597 mm	1080 mm	9.2 kg
BR Booklet Maker Finisher	769.2 mm	723 mm	1055.1 mm	60.9 kg
Dimensions and Weight (Packaged)	Width	Depth	Height	Weight
VersaLink® C8000/DT	833 mm	717 mm	852 mm	95 kg
High Capacity Feeder	526 mm	756 mm	491 mm	33.7 kg
Two Tray Module	830 mm	850 mm	400 mm	33 kg
Tandem Tray Module	830 mm	850 mm	400 mm	39 kg
Office Finisher	690 mm	1021 mm	654 mm	37 kg
Booklet Maker Finisher	507 mm	761 mm	437 mm	14 kg

Xerox® VersaLink® C8000 Colour Printer

BR Booklet Maker Finisher	764 mm	774 mm	1203 mm	77 kg
Horizontal Transport for BR Booklet Maker Finisher	533 mm	589 mm	319 mm	6.5 kg
Certifications				
To view the latest list of certifications, go to www.xerox.com/OfficeCertifications .				
Print				
First-print-out Time	As fast as 11 seconds colour			
	As fast as 11 seconds black and white			
Print Resolution	Up to 1200 x 2400 dpi			
Page Description Languages	Adobe® PostScript® 3™ PCL® 5c, 6 PDF XPS TIFF JPEG HP-GL			
Colour Management	Embedded spot colour table, Xerox Colour Corrections			
Maximum Print Area	4 mm from lead edge of paper, 2 mm from side and trail edges of paper			
Print Features	<ul style="list-style-type: none"> Application Defaults Banner Pages Enable / Disable Bi-directional Real-time Status Booklet Layout Colour Adjustments (lightness, contrast, saturation, colour balance) Colour Correction Draft Mode Finishing (requires finishing) Fit to new paper size Job Identification (Print ID or Banner, Print ID in margins on first page only or all pages) Job Monitoring (Client or Local User Interface) N-up Page Layout (up to 16 pages per sheet) Paper Selection by Attribute Personal Print Print Around Enable / Disable Print from USB Run Black Sample Set Saved Job Scaling Secure Print Skip Blank Pages Special Pages (exception page programming: covers, inserts, exceptions pages) Store and Recall Driver Settings Stored Jobs Deletion Two-sided Printing (as default) Watermark (predefined and custom) Xerox® Earth Smart Driver Settings 			
Print from USB	<ul style="list-style-type: none"> Allows walk-up printing from Type A USB port Supports direct printing from computer via Type B USB port Supported file formats: PDF, JPEG, TIFF, XPS, PDF/A 			

Xerox® VersaLink® C8000 Colour Printer

Operating Systems	<p>Windows® 7, 8, 8.1, 10 Windows Server 2008 SP2, Server 2008 R2 SP1, Server 2012, Server 2012 R2, Server 2016, Server 2019 macOS® 10.11, 10.12, 10.13 Citrix® Redhat® Enterprise Linux® Fedora Core IBM® AIX® HP-UX® Oracle® Solaris SUSE® SAP® UNIX®</p> <p>Note: For information about supported versions for the above operating systems, please visit our Drivers & Downloads page and specify your device at www.support.xerox.com.</p>
Fonts	<p>PostScript fonts: 136 PCL fonts: 83</p>
Xerox® Mobile Express Driver®	<p>Makes it easy for mobile users to find, use and manage Xerox® and non-Xerox® devices in every new location. Plug into a new network, and Mobile Express Driver automatically discovers available printers and provides status and capability information. Save a list of “favorite” printers for each location, store application print settings for use on any printer in any network, and greatly reduce mobile support calls to IT.</p>
Xerox® Global Print Driver®	<p>A truly universal print driver that lets IT administrators install, upgrade and manage Xerox® and non-Xerox® devices from a single driver. It provides a consistent, easy-to-use interface for end-users, reducing the number of support calls, and simplifying print services management.</p>
Xerox® Pull Print Driver	<p>Makes it easy for IT managers to qualify, deploy and manage all print devices using a single driver in a Pull Print environment. Uses a single queue and single driver. The Xerox® Pull Print Driver extends convenience across a broad range of printing assets. IT administrators no longer need to manage and configure multiple drivers. Used in conjunction with Equitrac Office®, Ysoft® SafeQ®, Pharos® and others.</p>
Mobile Solutions and Mobile Device Apps	
Apple® AirPrint®	<p>Print email, photos and important office documents directly from an Apple iPhone® or iPad® with no drivers to install and no cables to connect. With AirPrint, an iPhone or iPad automatically locates and connects to the AirPrint-enabled device over the office Wi-Fi network.</p>
Google Cloud Print™	<p>Google Cloud Print connects print devices to the web, enabling users to print the applications they use every day from smartphones, tablets, Chromebook™ notebook computers and any other web-connected device.</p>
Mopria® Certified	<p>ConnectKey® Technology-enabled print devices are Mopria® certified. Mopria certification ensures you can print wirelessly from your Mopria supported (Android™) smartphone, tablet and other mobile devices instantly and easily.</p>
@PrintByXerox	<p>@PrintByXerox is a free service that allows secure printing from any email-enabled device (computer, phone, tablet, iOS, Android™, Google® Chromebook™ and more) to a Xerox® printer or MFP using a single email address with no IT intervention. No training is needed. End-users simply send attachments to the email address and release them at the MFP panel.</p>
Xerox® Print Service Plug-in for Android™ (Free at Google Play™ Store)	<p>The Xerox® Print Service Plug-in for Android KitKat (4.4 or greater) devices streamlines mobile printing without third-party apps or additional print drivers. You can easily print photos, Web pages and documents when your mobile device is connected to printers using a wireless network. A robust print option set includes two-sided printing, stapling and secure code release. A free download is available from the Google Play™ store.</p>
Xerox® Workplace Suite and Xerox® Workplace Cloud	<p>Xerox® Workplace Solutions boost productivity and reduce costs with a modular print management and mobility solution. Control and manage your printer fleet while enabling mobile productivity with simplified workflows, convenience and security—for any brand printer, anywhere. Xerox® Workplace Solutions offer flexible license options to suit any size business with the ability to scale as you grow.</p> <ul style="list-style-type: none"> • Xerox® Workplace Suite: On site, your server • Xerox® Workplace Cloud: Simple setup, cloud administration <p>To learn more about the Xerox® Workplace Suite and Xerox® Workplace Cloud, visit www.xerox.com/Mobility.</p>

Xerox® VersaLink® C8000 Colour Printer

Software Solutions	
Xerox® ConnectKey® Apps (Found at the Xerox® App Gallery)	Increase user productivity by simplifying and shortening everyday tasks. Unlike traditional software, ConnectKey Apps do not require a dedicated server, PC or IT resource. Instead, simply download these lightweight, Serverless ConnectKey Apps to the device.
Security	
Security Features	<p>Access Controls AES 256-bit Encryption Audit Log Certificate Path Validation Certificate Revocation List (CRL)/Status Protocol (OCSP) Detection of external programme falsification (XCP Plug-in) Cisco® Identity Services Engine (ISE) Integration Domain Filtering FIPS 140-2 Firmware Verification Immediate Disk Overwrite* IP Address Filtering IPsec Network Authentication Port Filtering Pre-installed Self-Signed Certificates Role Based Permissions Secure Print Security Certificate Management Smart Card Enablement (CAC/PIV/.NET) SNMPv3 Status Protocol (OCSP) TLS/SSL</p> <p>*Requires HDD/Productivity Kit</p>
Accounting	
Xerox® Standard Accounting / Network Accounting (Standard)	
Tracking	Print usage
Accounting	<p>Xerox® Standard Accounting Tool Up to 1,000 User Accounts without HDD Up to 9,999 User Accounts with HDD Up to 500 General accounts</p> <p>Network Accounting (Job Based Accounting) Up to 1,000 User IDs; Up to 1,000 Account IDs without HDD Up to 60,000 User IDs; Up to 60,000 Account IDs with HDD Up to 14,000 accounting records (transactions)</p>
Features	Administrator can manage the feature via the Embedded Web Server.
Accounting Options – Network Accounting (Allows central server to manage all accounting)	
	<ul style="list-style-type: none"> Enhanced network accounting with up to the minute data on how the system is being used Comprehensive management and enterprise scale tracking and reporting of device print usage Numerous solutions are available through Xerox Alliance Partners. For details visit www.xerox.com Security enhancements include simultaneous support for HTTP/HTTPS protocols Device requests account authentication from third party server enabling larger databases of users and accounts Accept Authentication Login at control panel and pass to third party Networking Account
Paper Handling	
Bypass Tray	
Capacity⁴	100 sheets
Sizes	Custom sizes: 88.9 x 98.4 mm to 320 x 482.6 mm Banners: 88.9 x 98.4 mm to 320 x 1320.8 mm
Weights	Simplex and Duplex: 64 to 300 gsm

Xerox® VersaLink® C8000 Colour Printer

Types	Bond Plain Paper Cardstock Custom Envelopes Glossy Cardstock Hole Punched Labels Heavyweight Cardstock Heavyweight Glossy Cardstock Letterhead Lightweight Cardstock Lightweight Glossy Cardstock Pre-Printed Postcards Recycled
Tray 1 and 2	
Capacity⁴	520 sheets each
Sizes	Tray 1: 100 x 148 mm to 297 x 431.8 mm Tray 2: 100 x 148 mm to 320 x 457.2 mm
Weights	Simplex and Duplex: 64 to 300 gsm
Types	Bond Plain Paper Cardstock Custom Glossy Cardstock Hole Punched Labels Heavyweight Cardstock Heavyweight Glossy Cardstock Letterhead Lightweight Cardstock Lightweight Glossy Cardstock Pre-Printed Recycled
Two Tray Module	
Capacity⁴	1,040 sheets
Sizes	Custom sizes: 100 x 148 mm to 320 x 457.2 mm
Weights	Simplex and Duplex: 64 to 300 gsm
Types	Bond Plain Paper Cardstock Custom Glossy Cardstock Hole Punched Labels Heavyweight Cardstock Heavyweight Glossy Cardstock Letterhead Lightweight Cardstock Lightweight Glossy Cardstock Pre-Printed Recycled
Tandem Tray Module	
Capacity⁴	2,000 sheets
Sizes	A4, B5
Weights	Simplex and Duplex: 64 to 300 gsm

Xerox® VersaLink® C8000 Colour Printer

Types	Bond Plain Paper Cardstock Custom Glossy Cardstock Hole Punched Labels Heavyweight Cardstock Heavyweight Glossy Cardstock Letterhead Lightweight Cardstock Lightweight Glossy Cardstock Pre-Printed Recycled
High Capacity Feeder	
Capacity⁴	2,000 sheets
Sizes	A4, B5
Weights	64 to 216 gsm
Types	Bond Plain Paper Cardstock Custom Glossy Cardstock Hole Punched Letterhead Lightweight Cardstock Lightweight Glossy Cardstock Recycled
Envelope Tray – Replaces Tray 1 (Optional)	
Capacity⁴	Up to 50 envelopes
Sizes	DL, C4, C5, C6 Custom sizes: 90 x 98 mm to 241 x 332 mm
Total Capacity	
VersaLink® C8000/DT Capacity⁴	1,140 sheets
Maximum Capacity⁴	5,140 sheets
Finishing	
Output Trays	
Dual Offset Catch Tray (Standard when finishers are not attached)	500 sheets (without center tray) 2x 250 sheets (with center tray when offset is off) 2x 125 sheets (with center tray when offset is on)
Office Finisher (Optional)	
Capacity⁴	Stacking Tray: 2,000 sheets unstapled or 1,000 sheets single stapled or 750 sheets dual stapled (A4) (dual stapling only with optional booklet maker) Offset available for collated sets of standard size paper (A4 to A3)
Sizes	210 x 182 mm to 297 x 432 mm
Weights	60 to 220 gsm
Multi-position Stapling	50 sheets of 90 gsm
Hole Punch (Optional) Europe and Other Geographies:	Up to 65 lb cover (200 gsm) 2/4 hole punch

Xerox® VersaLink® C8000 Colour Printer

Booklet Maker for Office Finisher (Score/Crease, Saddle-stitch Staple) (Optional)	
Capacity⁴	40 booklets (2 to 15 sheets per booklet – 80 gsm or less)
Sizes	Letter – A4 SEF – B4 SEF Ledger – A3 SEF
Saddle-stitch Stapling	2 to 15 sheets/8-60 page booklets/60 to 90 gsm
Score / Crease	1 to 15 sheets/unstapled/60 to 105 gsm only
Optional BR Booklet Maker Finisher (Requires Horizontal Transport Kit)	
Capacity⁴	Offsetting Top Tray: 500 sheets of A4 unstapled Stacking Stapling Tray: 1,500 sheets of A4/A3 unstapled or 200 stapled sets of A4 (single-position stapling or dual or 4-position stapling) or 100 stapled sets of A3
Sizes	A6 to A3 for stacking B5 to A3 for stapling
Weights	60 to 300 gsm (coated and uncoated)
Stapling	Single and multiposition stapling Auto stapling (50 sheets maximum) – 90 gsm A3, A4, B4 and B5 sizes supported
Hole Punch Europe	2/4 hole punch 4 hole “Swedish” punch (optional)
Booklet Maker	Saddle-stitch 2 to 16 sheets (7 sheets at 106 to 176 gsm coated or 5 sheets at 177 to 220 gsm coated) Bi-fold up to 5 sheets A3, A4 supported
Device Management	
Network Protocols	TCP/IP: HTTP/HTTPS, Internet Printing Protocol, LPR/LPD, Raw Socket Printing/Port 9100, IPv4/IPv6, WSD, LDAP, Bonjour® / AirPrint™ Most protocols not in use can be disabled
Administrative Protocols	DHCP, SNMP, WINS, HTTP, HTTPS, TLS, SNTP, MDNS
Xerox® CentreWare® Web	
	<ul style="list-style-type: none"> • A Web-based server application for network administrators that permits web browser-based device management from any workstation, whether running Windows or UNIX or any other operating system • Works with any SNMP-managed printer from any manufacturer • Provides help with device discovery and installations, health checks and troubleshooting, and device upgrades, as well as basic accounting and asset management
Xerox® Embedded Web Server – Integrated Device Web Page	
Device Status	<ul style="list-style-type: none"> • Tray status/contents • Consumables status • Billing/Usage • Quick Links • Online Support
Print Queue Viewing	Job print queue management—view and delete
Job Submission	Print-ready files (PS, PCL, PDF, XPS, JPEG, TXT, PRN, TIF)
Device Administration	Allows simple, remote installation setting of configuration options and management of the device

Xerox® VersaLink® C8000 Colour Printer

Browsers	Microsoft® Internet Explorer® Microsoft Edge™ Mozilla™ Firefox® Apple® Safari® Google Chrome™	
Remote Services		
Automated Meter Reading (AMR)	Automates the process of collecting and submitting meter reads for tracking and billing of Xerox® device usage. Eliminates the need for time-consuming end-user involvement and ensures that meter reads are submitted to Xerox on time.	
Automated Supplies Replenishment (ASR)	Automatically orders supplies for Xerox output devices based on actual usage, eliminating the need to manually manage supplies inventory.	
MaintenanceAssistant	Offers a fast (and free) way to resolve potential issues and receive assistance and automate the troubleshooting/repair process. Diagnostic data is sent to Xerox®, allowing for problems to be solved faster with increased uptime.	
What's In The Box		
	<ul style="list-style-type: none"> • VersaLink® C8000 Colour Printer • Starter Capacity Print Cartridge: One of each (Cyan, Magenta, Yellow: 8,000 print capacity⁵, Black: 12,000 print capacity⁵) • Drum Cartridge – One of each (Cyan, Magenta, Yellow, & Black 190,000 print capacity)⁶ • Quick Use Guide • Install Guide • Software and Documentation CD (with Drivers, Warranty Statement and Safety Regulatory Recycle Disposal Guide) • Power Cord 	
Supplies and Accessories	Quantity	Part Number
Supplies		
Standard Capacity Toner Cartridges	Cyan: 7,600 standard pages ⁵ Magenta: 7,600 standard pages ⁵ Yellow: 7,600 standard pages ⁵ Black: 12,600 standard pages ⁵	106R04038 106R04039 106R04040 106R04041
High Capacity Toner Cartridges	Cyan: 16,500 standard pages ⁵ Magenta: 16,500 standard pages ⁵ Yellow: 16,500 standard pages ⁵ Black: 20,900 standard pages ⁵	106R04050 106R04051 106R04052 106R04053
Drum Cartridge	Cyan: 190,000 standard pages ⁶ Magenta: 190,000 standard pages ⁶ Yellow: 190,000 standard pages ⁶ Black: 190,000 standard pages ⁶	101R00602
Waste Cartridge	47,000 standard pages ⁶	108R01504
IBT Cleaner	160,000 standard pages ⁶	104R00256
Transfer Roller	200,000 standard pages ⁶	116R00015
Office Finisher Booklet Maker Cartridge (8 cartridges per container)	16,000 staples (2,000 each cartridge)	008R12897
Staple Refills for Office Finisher (3 refills per container)	15,000 staples (5,000 each refill)	008R12941
Staple Cartridges for BR Finisher and Office Finisher (1 cartridge per carton)	5,000 staples (5,000 each cartridge)	008R12964
Staple Cartridges for BR Booklet Maker (1 cartridge per carton)	5,000 staples (5,000 each cartridge)	008R13177

Xerox® VersaLink® C8000 Colour Printer

Accessories / Options	
Two Tray Module	097S04969
Tandem Tray Module	097S04970
High Capacity Feeder	097S04845
Envelope Tray (Replaces Tray 1)	497K17880
Office Finisher Gap Filler (required)	097S04848 497K17370
2/3 Hole Punch for Office Finisher	497K03860
2/4 Hole Punch for Office Finisher	497K03870
Booklet Maker for Office Finisher	497K03852
BR Booklet Maker Finisher with 2/3 Hole Punch	097S04981
BR Booklet Maker finisher with 2/4 Hole Punch	097S04982
Horizontal Transport for BR Finisher	497K17440
Swedish 4 Hole Punch for BR Finisher	497K14370
320 GB HDD	097S04971
Wireless Network Adapter Kit	497K16750
Internal Card Reader/RFID Kit	497K18120 (Western Hemisphere) 497K18140 (Eastern Hemisphere)

¹ Maximum volume capacity expected in any one month. Not expected to be sustained on a regular basis.

² Expected regular monthly throughput.

³ Power states defined per ENERGY STAR® Programme requirements for Imaging Equipment.

⁴ Paper capacities are based on 75 gsm stock; capacities will vary with different weight stocks.

⁵ Average standard pages. Declared Yield in accordance with ISO/IEC 19798. Yield will vary based on image, area coverage and print mode.

⁶ Approximate pages. Declared yield will vary depending on job run length, media size/orientation and machine speed. For more information visit: <http://www.office.xerox.com/Latest/SUPGL-01.pdf>.

Return spent imaging supplies through the Xerox® Green World Alliance® collection/reuse/recycling program. For more information, visit www.xerox.com/About-Xerox/Recycling.

For more information, visit us at www.xerox.com/Office.

Configurations vary by geography.