

# Xerox® VersaLink® C8000 Color Printer



The VersaLink® C8000 Color Printer is built on Xerox® ConnectKey® Technology. For more information, go to [www.ConnectKey.com](http://www.ConnectKey.com).

System Specifications	VersaLink® C8000
<b>One-Sided Speed</b> 8.5 x 11 in. / A4 8.5 x 11 in. / A4 SEF 8.5 x 14 in. / 216 x 356 mm 11 x 17 in. / A3 / 297 x 420 mm / 12 x 18 in / SRA3 / 320 x 450 mm	Up to 45 ppm (pages per minute) long edge feed (LEF) Up to 32 ppm Up to 26 ppm Up to 22 ppm
<b>Two-Sided Speed</b> 8.5 x 11 in. / A4 8.5 x 11 in. / A4 SEF 8.5 x 14 in. / 216 x 356 mm 11 x 17 in. / A3 / 297 x 420 mm / 12 x 18 in / SRA3 / 320 x 450 mm	Up to 45 ppm LEF Up to 32 ppm Up to 17 ppm Up to 15 ppm
<b>Monthly Duty Cycle<sup>1</sup></b>	Up to 205,000 pages / month
<b>Recommended Average Monthly Print Volume<sup>2</sup></b>	Up to 20,000 pages per month
<b>Hard Drive</b>	320 GB HDD (Optional)
<b>Processor</b>	1.6 GHz Dual-Core
<b>Memory</b>	4 GB
<b>Connectivity</b>	Ethernet 10/100/1000 Base-T, High-speed USB 3.0, Wi-Fi 802.11n/g/b/a and Wi-Fi Direct with optional Wi-Fi Kit (concurrent wired and wireless connections supported), NFC Tap-to-Pair
<b>Controller Features</b>	Configuration Cloning, Xerox Extensible Interface Platform®, Xerox App Gallery, Xerox® Standard Accounting, Network Accounting Enabled, Role Based Permissions, Convenience Authentication Enabled, Online Support
<b>User Interface Languages</b>	English, French, Italian, German, Spanish, Brazilian Portuguese, Russian, Dutch, Swedish, Danish, Finnish, Norwegian, Greek, Turkish, Polish, Czech, Hungarian, Romanian, Catalan

# Xerox® VersaLink® C8000 Color Printer

Device Specifications				
<b>Electrical Requirements</b>				
<b>North America</b>	Voltage: 110-127V +/-10 % Frequency: 50/60 Hz +/-3 %, 12A			
<b>Europe and Other Geographies</b>	Voltage: 220-240V +/- 10 % Frequency: 50/60 Hz +/-3 %, 10A			
<b>Power Consumption</b>				
<b>Printing<sup>3</sup></b>	For 110V: 2.30 kWh For 220V: 2.32 kWh			
<b>Standby Mode<sup>3</sup></b>	110V: 75.3 watts or less 220V: 73.8 watts or less			
<b>Sleep Mode<sup>3</sup></b>	110V: 0.48 watts or less 220V: 0.53 watts or less			
<b>Operating Environment</b>				
<b>Required Temperature Range (Storage)</b>	Below 48° C, and in compliance with MN2-810.13			
<b>Required Temperature Range (Operating)</b>	50° to 83° F (10° to 28° C) Must be 28° C or below if humidity is at 85 %			
<b>Required Relative Humidity</b>	15 % to 85 % Must be 62.5 % or below at 32° C			
<b>Sound Power Levels</b>	Printing: 6.63 B(A) or less Standby: 3.24 B(A) or less  <b>Full System (including finisher)</b> Printing: 7.56 B(A) Standby: 3.36 B(A)			
<b>Sound Pressure Levels</b>	Printing: 56.8 dB or less Standby: 15.4 dB or less  <b>Full System (including finisher)</b> Printing: 57.1 dB Standby: 15.2 dB			
<b>Boot Time (from Off to UI Ready)</b>	Less than 60 seconds			
<b>Warm-up Time (from Sleep to UI Ready)</b>	Less than 10 seconds (without HDD) Less than 16 seconds (with HDD)			
<b>Dimensions and Weight (Unpackaged)</b>	<b>Width</b>	<b>Depth</b>	<b>Height</b>	<b>Weight</b>
VersaLink® C8000	24.4 in. / 620 mm	28.5 in. / 723 mm	31.9 in. / 809.3 mm	178 lb. / 80.8 kg
Two Tray Module	26.3 in. / 668.5 mm	28.5 in. / 723 mm	10.3 in. / 261.2 mm	60.0 lb. / 27.2 kg
Tandem Tray Module	26.3 in. / 668.5 mm	28.5 in. / 723 mm	10.3 in. / 261.2 mm	74.5 lb. / 33.8 kg
High Capacity Feeder	15.3 in. / 389 mm	23.7 in. / 602.9 mm	15.0 in. / 380.01 mm	63.9 lb. / 29.0 kg
Office Finisher	22 in. / 559.8 mm	21.7 in. / 552 mm	39.8 in. / 1012 mm	61.7 lb. / 28.0 Kg
Booklet Maker Finisher	11.75 in. / 298.5 mm	23.5 in. / 597 mm	42.5 in. / 1080 mm	20.3 lb. / 9.2 Kg
BR Booklet Maker Finisher	30.28 in. / 769.2 mm	28.5 in. / 723 mm	41.5 in. / 1055.1 mm	134.3 lb. / 60.9 Kg

## Xerox® VersaLink® C8000 Color Printer

Dimensions and Weight (Packaged)	Width	Depth	Height	Weight
VersaLink® C8000	32.8 in. / 833 mm	28.2 in. / 717 mm	33.4 in. / 852 mm	209.4 lb. / 95 kg
High Capacity Feeder	20.7 in. / 526 mm	29.8 in. / 756 mm	19.3 in. / 491 mm	74.3 lb. / 33.7 kg
Two Tray Module	32.7 in. / 830 mm	33.5 in. / 850 mm	15.75 in. / 400 mm	72.7 lb. / 33 kg
Tandem Tray Module	32.7 in. / 830 mm	33.5 in. / 850 mm	15.75 in. / 400 mm	86 lb. / 39 kg
Office Finisher	27.2 in. / 690 mm	40.2 in. / 1021 mm	25.7 in. / 654 mm	82 lb. / 37 kg
Booklet Maker Finisher	20 in. / 507 mm	30 in. / 761 mm	17.2 in. / 437 mm	31 lb. / 14 kg
BR Booklet Maker Finisher	30 in. / 764 mm	30.5 in. / 774 mm	47.4 in. / 1203 mm	169.7 lb. / 77 kg
Horizontal Transport for BR Booklet Maker Finisher	21 in. / 533 mm	23.1 in. / 589 mm	12.6 in. / 319 mm	14.3 lb. / 6.5 kg

### Certifications

To view the latest list of certifications, go to [www.xerox.com/OfficeCertifications](http://www.xerox.com/OfficeCertifications).

### Print

<b>First-print-out Time</b>	As fast as 11 seconds color
	As fast as 11 seconds black and white
<b>Print Resolution</b>	Up to 1200 x 2400 dpi
<b>Page Description Languages</b>	Adobe® PostScript® 3™ PCL® 5c, 6 PDF XPS TIFF JPEG HP-GL
<b>Color Management</b>	Embedded spot color table, Xerox Color Corrections
<b>Maximum Print Area</b>	4 mm from Lead edge of paper, 2 mm from Side and Trail edges of paper

## Xerox® VersaLink® C8000 Color Printer

<b>Print Features</b>	<ul style="list-style-type: none"> <li>Application Defaults</li> <li>Banner Pages Enable / Disable</li> <li>Bi-directional Real-time Status</li> <li>Booklet Layout</li> <li>Color Adjustments (lightness, contrast, saturation, color balance)</li> <li>Color Correction</li> <li>Draft Mode</li> <li>Finishing (requires finishing)</li> <li>Fit to New Paper Size</li> <li>Job Identification (Print ID or Banner, Print ID in margins on first page only or all pages)</li> <li>Job Monitoring (Client or Local User Interface)</li> <li>N-up Page Layout (up to 16 pages per sheet)</li> <li>Paper Selection by Attribute</li> <li>Personal Print</li> <li>Print Around Enable / Disable</li> <li>Print from USB</li> <li>Run Black</li> <li>Sample Set</li> <li>Saved Job</li> <li>Scaling</li> <li>Secure Print</li> <li>Skip Blank Pages</li> <li>Special Pages (exception page programming: covers, inserts, exceptions pages)</li> <li>Store and Recall Driver Settings</li> <li>Stored Jobs Deletion</li> <li>Two-sided Printing (as default)</li> <li>Watermark (predefined and custom)</li> <li>Xerox® Earth Smart Driver Settings</li> </ul>
<b>Print from USB</b>	<ul style="list-style-type: none"> <li>Allows walk-up printing from Type A USB port</li> <li>Supports direct printing from computer via Type B USB port</li> <li>Supported file formats: PDF, JPEG, TIFF, XPS, PDF/A</li> </ul>
<b>Operating Systems</b>	<ul style="list-style-type: none"> <li>Windows® 7, 8, 8.1, 10</li> <li>Windows Server 2008 SP2, Server 2008 R2 SP1, Server 2012, Server 2012 R2, Server 2016, Server 2019</li> <li>macOS® 10.11, 10.12, 10.13</li> <li>Citrix®</li> <li>Redhat® Enterprise Linux®</li> <li>Fedora Core</li> <li>IBM® AIX®</li> <li>HP-UX®</li> <li>Oracle® Solaris</li> <li>SUSE®</li> <li>SAP®</li> <li>UNIX®</li> </ul> <p>Note: For information about supported versions for the above operating systems, please visit our Drivers &amp; Downloads page and specify your device at <a href="http://www.support.xerox.com">www.support.xerox.com</a>.</p>
<b>Fonts</b>	<ul style="list-style-type: none"> <li>PostScript fonts: 136</li> <li>PCL fonts: 83</li> </ul>
<b>Xerox® Mobile Express Driver®</b>	<p>Makes it easy for mobile users to find, use and manage Xerox® and non-Xerox® devices in every new location. Plug into a new network, and Mobile Express Driver® automatically discovers available printers and provides status and capability information. Save a list of “favorite” printers for each location, store application print settings for use on any printer in any network, and greatly reduce mobile support calls to IT.</p>
<b>Xerox® Global Print Driver®</b>	<p>A truly universal print driver that lets IT administrators install, upgrade and manage Xerox® and non-Xerox® devices from a single driver. It provides a consistent, easy-to-use interface for end-users, reducing the number of support calls, and simplifying print services management.</p>
<b>Xerox® Pull Print Driver</b>	<p>Makes it easy for IT managers to qualify, deploy and manage all print devices using a single driver in a Pull Print environment. Uses a single queue and single driver. The Xerox® Pull Print Driver extends convenience across a broad range of printing assets. IT administrators no longer need to manage and configure multiple drivers. Used in conjunction with Equitrac Office®, Ysoft® SafeQ®, Pharos® and others.</p>

## Xerox® VersaLink® C8000 Color Printer

Mobile Solutions and Mobile Device Apps	
<b>Apple® AirPrint®</b>	Print email, photos and important office documents directly from an Apple iPhone® or iPad® with no drivers to install and no cables to connect. With AirPrint, an iPhone or iPad automatically locates and connects to the AirPrint-enabled device over the office Wi-Fi network.
<b>Google Cloud Print™</b>	Google Cloud Print connects print devices to the web, enabling users to print the applications they use every day from smartphones, tablets, Chromebook™ notebook computers and any other web-connected device.
<b>Mopria® Certified</b>	ConnectKey® Technology-enabled print devices are Mopria® certified. Mopria® certification ensures you can print wirelessly from your Mopria® supported (Android™) smartphone, tablet and other mobile devices instantly and easily.
<b>@PrintByXerox</b>	@PrintByXerox is a free service that allows secure printing from any email-enabled device (computer, phone, tablet, iOS, Android™, Google® Chromebook™ and more) to a Xerox® printer or MFP using a single email address with no IT intervention. No training is needed. End-users simply send attachments to the email address and release them at the MFP panel.
<b>Xerox® Print Service Plug-in for Android™ (Free at Google Play™ Store)</b>	The Xerox® Print Service Plug-in for Android KitKat (4.4 or greater) devices streamlines mobile printing without third-party apps or additional print drivers. You can easily print photos, Web pages and documents when your mobile device is connected to printers using a wireless network. A robust print option set includes two-sided printing, stapling and secure code release. A free download is available from the Google Play™ store.
<b>Xerox® Workplace Suite and Xerox® Workplace Cloud</b>	<p>Xerox® Workplace Solutions boost productivity and reduce costs with a modular print management and mobility solution. Control and manage your printer fleet while enabling mobile productivity with simplified workflows, convenience and security—for any brand printer, anywhere. Xerox® Workplace Solutions offer flexible license options to suit any size business with the ability to scale as you grow.</p> <ul style="list-style-type: none"> <li>• Xerox® Workplace Suite: On site, your server</li> <li>• Xerox® Workplace Cloud: Simple setup, cloud administration</li> </ul> <p>To learn more about the Xerox® Workplace Suite and Xerox® Workplace Cloud, visit <a href="http://www.xerox.com/Mobility">www.xerox.com/Mobility</a>.</p>
Software Solutions	
<b>Xerox® ConnectKey® Apps (Found at the Xerox App Gallery)</b>	Increase user productivity by simplifying and shortening everyday tasks. Unlike traditional software, ConnectKey® Apps do not require a dedicated server, PC or IT resource. Instead, simply download these lightweight, Serverless ConnectKey® Apps to the device.
Security	
<b>Security Features</b>	<p>Access Controls            AES 256-bit Encryption            Audit Log            Certificate Path Validation            Certificate Revocation List (CRL)/Status Protocol (OCSP)            Detection of External Program Falsification (XCP Plug-in)            Cisco® Identity Services Engine (ISE) Integration            Domain Filtering            FIPS 140-2            Firmware Verification            Immediate Disk Overwrite*            IP Address Filtering            IPsec            Network Authentication            Port Filtering            Pre-installed Self-Signed Certificates            Role Based Permissions            Secure Print            Security Certificate Management            Smart Card Enablement (CAC/PIV/.NET)            SNMPv3            Status Protocol (OCSP)            TLS/SSL</p> <p>*Requires HDD/Productivity Kit</p>

# Xerox® VersaLink® C8000 Color Printer

Accounting	
<b>Xerox® Standard Accounting / Network Accounting (Standard)</b>	
<b>Tracking</b>	Print usage
<b>Accounting</b>	<p><b>Xerox® Standard Accounting Tool</b>            Up to 1,000 User Accounts without HDD            Up to 9,999 User Accounts with HDD            Up to 500 General Accounts</p> <p><b>Network Accounting (Job Based Accounting)</b>            Up to 1,000 User IDs; Up to 1,000 Account IDs without HDD            Up to 60,000 User IDs; Up to 60,000 Account IDs with HDD            Up to 14,000 Accounting Records (transactions)</p>
<b>Features</b>	Administrator can manage the feature via the Embedded Web Server.
<b>Accounting Options – Network Accounting (Allows central server to manage all accounting)</b>	
	<ul style="list-style-type: none"> <li>• Enhanced network accounting with up to the minute data on how the system is being used</li> <li>• Comprehensive management and enterprise scale tracking and reporting of device print usage</li> <li>• Numerous solutions are available through Xerox Alliance Partners. For details visit <a href="http://www.xerox.com">www.xerox.com</a></li> <li>• Security enhancements include simultaneous support for HTTP/HTTPS protocols</li> <li>• Device requests account authentication from third party server enabling larger databases of users and accounts</li> <li>• Accept Authentication Login at control panel and pass to third party Networking Account</li> </ul>
Paper Handling	
<b>Bypass Tray</b>	
<b>Capacity<sup>4</sup></b>	100 sheets
<b>Sizes</b>	Custom sizes: 3.5 x 3.9 in. to 12.6 x 19 in./88.9 x 98.4 mm to 320 x 482.6 mm Banners: 3.5 x 3.9 in. to 12.6 x 52 in./88.9 x 98.4 mm to 320 x 1320.8 mm
<b>Weights</b>	Simplex and Duplex: 18 lb. bond to 110 lb. cover/64 to 300 gsm
<b>Types</b>	Bond Plain Paper Cardstock Custom Envelopes Glossy Cardstock Hole Punched Labels Heavyweight Cardstock Heavyweight Glossy Cardstock Letterhead Lightweight Cardstock Lightweight Glossy Cardstock Pre-Printed Postcards Recycled
<b>Tray 1 and 2</b>	
<b>Capacity<sup>4</sup></b>	520 sheets each
<b>Sizes</b>	Tray 1: 3.9 x 5.8 in. to 11.7 x 17 in./100 x 148 mm to 297 x 431.8 mm Tray 2: 3.9 x 5.8 in. to 12.6 x 18 in./100 x 148 mm to 320 x 457.2 mm
<b>Weights</b>	Simplex and Duplex: 18 lb. bond to 110 lb. cover/64 to 300 gsm

# Xerox® VersaLink® C8000 Color Printer

<b>Types</b>	<ul style="list-style-type: none"> <li>Bond</li> <li>Plain Paper</li> <li>Cardstock</li> <li>Custom</li> <li>Glossy Cardstock</li> <li>Hole Punched</li> <li>Labels</li> <li>Heavyweight Cardstock</li> <li>Heavyweight Glossy Cardstock</li> <li>Letterhead</li> <li>Lightweight Cardstock</li> <li>Lightweight Glossy Cardstock</li> <li>Pre-Printed</li> <li>Recycled</li> </ul>
<b>Two Tray Module</b>	
<b>Capacity<sup>4</sup></b>	1,040 sheets
<b>Sizes</b>	Custom sizes: 3.9 x 5.8 in. to 12.6 x 18 in./100 x 148 mm to 320 x 457.2 mm
<b>Weights</b>	Simplex and Duplex: 18 lb. bond to 110 lb. cover/64 to 300 gsm
<b>Types</b>	<ul style="list-style-type: none"> <li>Bond</li> <li>Plain Paper</li> <li>Cardstock</li> <li>Custom</li> <li>Glossy Cardstock</li> <li>Hole Punched</li> <li>Labels</li> <li>Heavyweight Cardstock</li> <li>Heavyweight Glossy Cardstock</li> <li>Letterhead</li> <li>Lightweight Cardstock</li> <li>Lightweight Glossy Cardstock</li> <li>Pre-Printed</li> <li>Recycled</li> </ul>
<b>Tandem Tray Module</b>	
<b>Capacity<sup>4</sup></b>	2,000 sheets
<b>Sizes</b>	8.5 x 11 in., 7.25 x 10.5 in./A4, B5
<b>Weights</b>	Simplex and Duplex: 18 lb. bond to 110 lb. cover/64 to 300 gsm
<b>Types</b>	<ul style="list-style-type: none"> <li>Bond</li> <li>Plain Paper</li> <li>Cardstock</li> <li>Custom</li> <li>Glossy Cardstock</li> <li>Hole Punched</li> <li>Labels</li> <li>Heavyweight Cardstock</li> <li>Heavyweight Glossy Cardstock</li> <li>Letterhead</li> <li>Lightweight Cardstock</li> <li>Lightweight Glossy Cardstock</li> <li>Pre-Printed</li> <li>Recycled</li> </ul>

## Xerox® VersaLink® C8000 Color Printer

High Capacity Feeder	
Capacity <sup>4</sup>	2,000 sheets
Sizes	8.5 x 11 in., 7.25 x 10.5 in./A4, B5
Weights	18 lb. bond to 95 lb. cover/64 to 216 gsm
Types	Bond Plain Paper Cardstock Custom Glossy Cardstock Hole Punched Letterhead Lightweight Cardstock Lightweight Glossy Cardstock Recycled
Envelope Tray – Replaces Tray 1 (Optional)	
Capacity <sup>4</sup>	Up to 50 envelopes
Sizes	#10 commercial, Monarch, DL, C4, C5, C6 Custom sizes: 3.5 x 3.85 in. to 9.5 x 13.1 in./90 x 98 mm to 241 x 332 mm
Total Capacity	
VersaLink® C8000 Capacity <sup>4</sup>	1,140 sheets
Maximum Capacity <sup>4</sup>	5,140 sheets
Finishing	
Output Trays	
Dual Offset Catch Tray (Standard when finishers are not attached)	500 sheets (without center tray) 2x 250 sheets (with center tray when offset is off) 2x 125 sheets (with center tray when offset is on)
Office Finisher (Optional)	
Capacity <sup>4</sup>	Stacking Tray: 2,000 sheets unstapled or 1,000 sheets single stapled or 750 sheets dual stapled (8.5 x 11 in. / A4) (dual stapling only with optional booklet maker) Offset available for collated sets of standard size paper (8.5 x 11 in. / A4 to 11 x 17 in. / A3)
Sizes	8.3 x 7.2 in. to 11.7 x 17 in./210 x 182 mm to 297 x 432 mm
Weights	18 lb. bond to 80 lb. cover/60 to 220 gsm
Multi-position Stapling	50 sheets of 24 lb. bond/90 gsm
Hole Punch (Optional) North America: Europe and Other Geographies:	Up to 65 lb cover (200 gsm) 2/3 hole punch 2/4 hole punch
Booklet Maker for Office Finisher (Score/Crease, Saddle-stitch Staple) (Optional)	
Capacity <sup>4</sup>	40 booklets (2 to 15 sheets per booklet – 20 lb./80 gsm or less)
Sizes	Letter – 8.5 x 11 in./A4 SEF Legal – 8.5 x 14 in./B4 SEF Ledger – 11 x 17 in./A3 SEF
Saddle-stitch Stapling	2 to 15 sheets/8-60 page booklet 18 lb. bond to 24 lb. bond/60 to 90 gsm
Score / Crease	1 to 15 sheets/unstapled/60 to 105 gsm only



## Xerox® VersaLink® C8000 Color Printer

Optional BR Booklet Maker Finisher (Requires Horizontal Transport Kit)	
<b>Capacity<sup>4</sup></b>	Offsetting Top Tray: 500 sheets of 8.5 x 11 in./A4 unstapled Stacking Stapling Tray: 1,500 sheets of 8.5 x 11 in./11 x 17 in./A4/A3 unstapled or 200 stapled sets of 8.5 x 11 in./A4 (single-position stapling or dual or 4-position stapling) or 100 stapled sets of 11 x 17 in./A3
<b>Sizes</b>	4 x 6 in. to 11 x 17 in./A6 to A3 for stacking 7.25 x 10.5 in. to 11 x 17 in./B5 to A3 for stapling
<b>Weights</b>	16 bond to 110 lb. cover/60 to 300 gsm (coated and uncoated)
<b>Stapling</b>	Single and multiposition stapling Auto stapling (50 sheets maximum) – 24 lb. / 90 gsm Letter, Legal, Tabloid, A3, A4, B4 and B5 sizes supported
<b>Hole Punch</b> North America Europe	2/3 hole punch 2/4 hole punch 4 hole “Swedish” punch (optional)
<b>Booklet Maker</b>	Saddle-stitch 2 to 16 sheets (7 sheets at 106 to 176 gsm coated or 5 sheets at 177 to 220 gsm coated) Bi-fold up to 5 sheets Letter, Legal, Tabloid, A3, A4 supported
Device Management	
<b>Network Protocols</b>	TCP/IP: HTTP/HTTPS, Internet Printing Protocol, LPR/LPD, Raw Socket Printing/Port 9100, IPv4/IPv6, WSD LDAP Bonjour® / AirPrint™ Most protocols not in use can be disabled
<b>Administrative Protocols</b>	DHCP, SNMP, WINS, HTTP, HTTPS, TLS, SNTP, MDNS
Xerox® CentreWare® Web	
	<ul style="list-style-type: none"> <li>• A web-based server application for network administrators that permits web browser-based device management from any workstation, whether running Windows or UNIX or any other operating system</li> <li>• Works with any SNMP-managed printer from any manufacturer</li> <li>• Provides help with device discovery and installations, health checks and troubleshooting, and device upgrades, as well as basic accounting and asset management</li> </ul>
Xerox® Embedded Web Server – Integrated Device Web Page	
<b>Device Status</b>	<ul style="list-style-type: none"> <li>• Tray Status / Contents</li> <li>• Consumables Status</li> <li>• Billing / Usage</li> <li>• Quick Links</li> <li>• Online Support</li> </ul>
<b>Print Queue Viewing</b>	Job print queue management — view and delete
<b>Job Submission</b>	Print-ready files (PS, PCL, PDF, XPS, JPEG, TXT, PRN, TIF)
<b>Device Administration</b>	Allows simple, remote installation setting of configuration options and management of the device
<b>Browsers</b>	Microsoft® Internet Explorer® Microsoft Edge™ Mozilla™ Firefox® Apple® Safari® Google Chrome™

## Xerox® VersaLink® C8000 Color Printer

Remote Services		
<b>Xerox® Automatic Meter Readings (AMR)</b>	Automates the process of collecting and submitting meter reads for tracking and billing of Xerox® device usage. Eliminates the need for time-consuming end-user involvement and ensures that meter reads are submitted to Xerox on time.	
<b>Xerox® Automatic Supplies Replenishment (ASR)</b>	Automatically orders supplies for Xerox® output devices based on actual usage, eliminating the need to manually manage supplies inventory.	
What's In The Box		
	<ul style="list-style-type: none"> <li>• VersaLink® C8000 Color Printer</li> <li>• Starter Capacity Print Cartridge: One of each (Cyan, Magenta, Yellow): 8,000 print capacity<sup>5</sup>, Black: 12,000 print capacity<sup>5</sup></li> <li>• Drum Cartridge – One of each (Cyan, Magenta, Yellow, &amp; Black 190,000 print capacity)<sup>6</sup></li> <li>• Quick Use Guide</li> <li>• Install Guide</li> <li>• Software and Documentation CD (with Drivers, Warranty Statement and Safety Regulatory Recycle Disposal Guide)</li> <li>• Power Cord</li> </ul>	
Supplies and Accessories	Quantity	Part Number
Supplies		
<b>Standard Capacity Toner Cartridges</b>	Cyan: 7,600 standard pages <sup>5</sup> Magenta: 7,600 standard pages <sup>5</sup> Yellow: 7,600 standard pages <sup>5</sup> Black: 12,600 standard pages <sup>5</sup>	106R04034 106R04035 106R04036 106R04037
<b>High Capacity Toner Cartridges</b>	Cyan: 16,500 standard pages <sup>5</sup> Magenta: 16,500 standard pages <sup>5</sup> Yellow: 16,500 standard pages <sup>5</sup> Black: 20,900 standard pages <sup>5</sup>	106R04046 106R04047 106R04048 106R04049
<b>Drum Cartridge</b>	Cyan: 190,000 standard pages <sup>6</sup> Magenta: 190,000 standard pages <sup>6</sup> Yellow: 190,000 standard pages <sup>6</sup> Black: 190,000 standard pages <sup>6</sup>	101R00602
<b>Waste Cartridge</b>	47,000 standard pages <sup>6</sup>	108R01504
<b>IBT Cleaner</b>	160,000 standard pages <sup>6</sup>	104R00256
<b>Transfer Roller</b>	200,000 standard pages <sup>6</sup>	116R00015
<b>Office Finisher Booklet Maker Cartridge (8 cartridges per container)</b>	16,000 staples (2,000 each cartridge)	008R12897
<b>Staple Refills for Office Finisher (3 refills per container)</b>	15,000 staples (5,000 each refill)	008R12941
<b>Staple Cartridges for BR Finisher and Office Finisher (1 cartridge per carton)</b>	5,000 staples (5,000 each cartridge)	008R12964
<b>Staple Cartridges for BR Booklet Maker (1 cartridge per carton)</b>	5,000 staples (5,000 each cartridge)	008R13177

# Xerox® VersaLink® C8000 Color Printer

Accessories / Options	
Two Tray Module	097S04969
Tandem Tray Module	097S04970
High Capacity Feeder	097S04845
Envelope Tray (Replaces Tray 1)	497K17880
Office Finisher Gap Filler (required)	097S04848 497K17370
2/3 Hole Punch for Office Finisher	497K03860
2/4 Hole Punch for Office Finisher	497K03870
Booklet Maker for Office Finisher	497K03852
BR Booklet Maker Finisher with 2/3 Hole Punch	097S04981
BR Booklet Maker finisher with 2/4 Hole Punch	097S04982
Horizontal Transport for BR Finisher	497K17440
Swedish 4 Hole Punch for BR Finisher	497K14370
320 GB HDD	097S04971
Wireless Network Adapter Kit	497K16750
Internal Card Reader/RFID Kit	497K18120 (Western Hemisphere) 497K18140 (Eastern Hemisphere)

<sup>1</sup> Maximum volume capacity expected in any one month. Not expected to be sustained on a regular basis.

<sup>2</sup> Expected regular monthly throughput.

<sup>3</sup> Power states defined per ENERGY STAR® Program requirements for Imaging Equipment.

<sup>4</sup> Paper capacities are based on 20 lb./75 gsm stock; capacities will vary with different weight stocks.

<sup>5</sup> Average standard pages. Declared Yield in accordance with ISO/IEC 19798. Yield will vary based on image, area coverage and print mode.

<sup>6</sup> Approximate pages. Declared yield will vary depending on job run length, media size/orientation and machine speed. For more information visit: <https://www.office.xerox.com/Latest/SUPGL-01.pdf>.

Return spent imaging supplies through the Xerox® Green World Alliance® collection/reuse/recycling program. For more information, visit [www.xerox.com/About-Xerox/Recycling](http://www.xerox.com/About-Xerox/Recycling).

For more information, visit us at [www.xerox.com/Office](http://www.xerox.com/Office).

Configurations vary by geography.