



Xerox WorkCentre M15 / M15i Multifunction Statement of Volatility

The chart below shows the corresponding memory types for the Xerox WorkCentre M15 / M15i Multifunction. Please note, on the M15i there is a residual of customer scan, copy, print & fax data retained in the device when the power is turned off.

However, this data can be cleared from the machine by using a front panel sequence to selectively clear buffers. See note # 4 below for additional detail.

Model Number	Memory Type	Volatility	User Data
M15	SDRAM (scan, copy print buffer @ 16 MB)	Volatile	Yes ¹
	Flash / ROM	Non-Volatile	No ³
	SDRAM (battery backed @ 128 KB)	Non-Volatile	No ²
M15i	SDRAM (battery backed scan, copy, print & fax buffers @ 16 MB and 4 MB for font storage)	Non-Volatile	No ⁴
	Flash / ROM	Non-Volatile	No ³
	SDRAM (battery backed @ 128 KB)	Non-Volatile	No ²

Notes:

- ¹ Will lose information when device is powered off for 10 seconds or more.
- ² Contains printer configuration and operational parameters. It does not contain user print, copy or scan data or images.
- ³ Is used for firmware code and contains no user or image data.
- ⁴ Contains user and or scan/copy/print/FAX image data. There is a "memory clear" function under "System Admin" that allows a user to manually clear scan, copy, print & fax buffers of residual image data.